

Technical Reference

020-101448-01

D4KLH-60 Serial API Commands

NOTICES

COPYRIGHT AND TRADEMARKS

Copyright ©2015 Christie Digital Systems USA Inc. All rights reserved.

All brand names and product names are trademarks, registered trademarks or trade names of their respective holders.

GENERAL

Every effort has been made to ensure accuracy, however in some cases changes in the products or availability could occur which may not be reflected in this document. Christie reserves the right to make changes to specifications at any time without notice. Performance specifications are typical, but may vary depending on conditions beyond Christie's control such as maintenance of the product in proper working conditions. Performance specifications are based on information available at the time of printing. Christie makes no warranty of any kind with regard to this material, including, but not limited to, implied warranties of fitness for a particular purpose. Christie will not be liable for errors contained herein or for incidental or consequential damages in connection with the performance or use of this material. Canadian manufacturing facility is ISO 9001 and 14001 certified.

WARRANTY

Products are warranted under Christie's standard limited warranty, the complete details of which are available by contacting your Christie dealer or Christie. In addition to the other limitations that may be specified in Christie's standard limited warranty and, to the extent relevant or applicable to your product, the warranty does not cover:

- a. Problems or damage occurring during shipment, in either direction.
- b. Projector lamps (See Christie's separate lamp program policy).
- c. Problems or damage caused by use of a projector lamp beyond the recommended lamp life, or use of a lamp other than a Christie lamp supplied by Christie or an authorized distributor of Christie lamps.
- d. Problems or damage caused by combination of a product with non-Christie equipment, such as distribution systems, cameras, DVD players, etc., or use of a product with any non-Christie interface device.
- e. Problems or damage caused by the use of any lamp, replacement part or component purchased or obtained from an unauthorized distributor of Christie lamps, replacement parts or components including, without limitation, any distributor offering Christie lamps, replacement parts or components through the internet (confirmation of authorized distributors may be obtained from Christie).
- f. Problems or damage caused by misuse, improper power source, accident, fire, flood, lightning, earthquake or other natural disaster.
- g. Problems or damage caused by improper installation/alignment, or by equipment modification, if by other than Christie service personnel or a Christie authorized repair service provider.
- h. Problems or damage caused by use of a product on a motion platform or other movable device where such product has not been designed, modified or approved by Christie for such use.
- i. Problems or damage caused by use of a projector in the presence of an oil-based fog machine or laser-based lighting that is unrelated to the projector.
- j. For LCD projectors, the warranty period specified in the warranty applies only where the LCD projector is in "normal use" which means the LCD projector is not used more than 8 hours a day, 5 days a week.
- k. Except where the product is designed for outdoor use, problems or damage caused by use of the product outdoors unless such product is protected from precipitation or other adverse weather or environmental conditions and the ambient temperature is within the recommended ambient temperature set forth in the specifications for such product.
- l. Image retention on LCD flat panels.
- m. Defects caused by normal wear and tear or otherwise due to normal aging of a product.

The warranty does not apply to any product where the serial number has been removed or obliterated. The warranty also does not apply to any product sold by a reseller to an end user outside of the country where the reseller is located unless (i) Christie has an office in the country where the end user is located or (ii) the required international warranty fee has been paid.

The warranty does not obligate Christie to provide any on site warranty service at the product site location.

PREVENTATIVE MAINTENANCE

Preventative maintenance is an important part of the continued and proper operation of your product. Please see the Maintenance section for specific maintenance items as they relate to your product. Failure to perform maintenance as required, and in accordance with the maintenance schedule specified by Christie, will void the warranty.


REGULATORY

The product has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the product is operated in a commercial environment. The product generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of the product in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at the user's own expense.

CAN ICES-3 (A) / NMB-3 (A)

이 기기는 업무용 (A 급) 으로 전자파적합등록을 한 기기이오니 판매자 또는 사용자는 이점을 주의하시기 바라며, 가정 외의 지역에서 사용하는 것을 목적으로 합니다.

Environmental

The product is designed and manufactured with high-quality materials and components that can be recycled and reused. This symbol  means that electrical and electronic equipment, at their end-of-life, should be disposed of separately from regular waste. Please dispose of the product appropriately and according to local regulations. In the European Union, there are separate collection systems for used electrical and electronic products. Please help us to conserve the environment we live in!

Content

D4KLH-60 Serial API	5
Documentation Conventions	5
ADR–Projector Address	5
ALC–Ambient Light Correction	6
ASU–Auto Setup	6
BDR–Baud Rate	6
BGC–Base Gamma Curve	7
BST–Built-in Self Test	8
CCA–Color Adjustment	9
CHA–Channel	12
CLE–Color Enable	13
CSP–Color Space Selection	13
DEF–Factory Defaults	14
DTL–Sharpness	14
EBB–Black Level Blending	14
EBL–Edge Blending Selection	15
EDO–EDID Override	15
EME–Enable Asynchronous Serial Messages	16
ETP–Engine Test Pattern	16
EVT–Event Manager	17
FCS–Lens Focus Position Adjustment	19
FRD–Frame Delay	19
FRZ–Image Freeze	20
GAM–Gamma Power Value	21
ITP–Internal Test Pattern	21
LCB–Lens Motor Calibration	23
LHO–Lens Horizontal Position Adjustment	23
LMV–Lens Move	24
LOE–Video Loop Out Enable	25
LVO–Lens Vertical Position Adjustment	25
NET–Network Setup	25
NTR–Network Routing	26
PNG–Ping	27
PRO–Profile	27

PWR–Power	28
RAL–Remote Access Level	29
SHU–Shutter	29
SNM–SNMP Configuration	30
SOR–Screen Orientation	30
SST–Status	31
SZP–Size and Position	32
TMD–Time and Date	32
UID–User ID	33
WRP–Warp Selection	33
ZOM–Lens Zoom Position Adjustment	34
Asynchronous messages	35

D4KLH-60 Serial API

The D4KLH-60 serial API commands can be used to modify projector settings.

Documentation Conventions

Convention	Description
Command Sequence Comment	Comment to provide sequence descriptions
(Command/subcode)	Command/subcode sent to the projector
<i>(Response)</i>	Response from the projector
<required arguments>	Mandatory argument for a serial command
[option arguments]	Optional argument for a serial command

ADR–Projector Address

Sets the projector address to target commands to a specific projector when communicating using the Christie Serial Protocol. This command also helps to identify where a response or asynchronous message originates from.

Generally, this command is used for projectors that are daisy-chained together using the RS232 style communication.

Commands

Command	Description	Values
ADR <value>	Sets the projector address to <value>.	0 to 999 65535 = Reserved broadcast address

Examples

Set all devices to address 0.

```
(65535 ADR 0)
```

Set first device at address 0 to address to 5.

(0 ADR 5)

Query address for all devices and return results to address 1001.

(65535 1001ADR?)

(01001 00005ADR!005)

ALC–Ambient Light Correction

Adjusts the image to help compensate for brighter or darker ambient light conditions.

Commands

Command	Description	Values
ALC <value>	Adjusts the image to help compensate for ambient light conditions.	0 = No correction 1 to 100 = Adjusts the image for darker environments -1 to -100 = Adjusts the image for brighter environments

ASU–Auto Setup

Automatically readjusts various video controls for the active video source to produce an optimal image on screen.

Commands

Command	Description	Values
ASU	Performs auto setup on the active video source.	-

Examples

Perform auto setup on the active video source.

(ASU)

BDR–Baud Rate

Sets the baud rate for any of the three serial ports on the projector.

Commands

Command	Description	Values
BDR+PRTA <value>	Sets the baud rate for the RS232-IN port.	1 = 2400 2 = 9600
BDR+PRTB <value>	Sets the baud rate for the RS232-OUT port.	3 = 19200 4 = 38400
BDR+PRTC <value>	Sets the baud rate for the RS422 port.	5 = 57600 6 = 115200 (Default baud rate on each port)

Examples

Set baud rate on port A to 115200 bits per second.

(BDR+PRTA 6)

Verify that RS232-IN is set to 115200bps.

(BDR+PRTA?)

(BDR+PRTA!006 "115200")

BGC—Base Gamma Curve

Applies a predefined gamma transfer function to the image.

Commands

Command	Description	Values
BGC <value>	Applies a predefined gamma transfer function to the image. Note: The Power Law Function is defined by the GAM—Gamma Power Law Exponent command.	0 = sRGB (Default) 1 = ITU-R BT.709 2 = Power Law Function

Examples

Select the sRGB gamma transfer function

(BGC 0)

Select a Power Law Function with a 2.6 Exponent.

(BGC 2)

(GAM 2600)

BST–Built-in Self Test

Performs a number of self-checks in the projector that can be safely executed either in standby, on, or cool down mode. Do not execute this command while the projector is warming up.

Commands

Command	Description	Values
BST?L	Returns a list of available test suites. (Read-only)	-
BST <suite>	Executes the test suite specified, where <suite> is numerical.	suite = One of the indices from BST?L
BST+TEST?L	Returns a list of available tests. (Read-only)	-
BST+TEST <index>	Executes the specified test.	index = One of the indices from BST+TEST?L

Examples

Retrieve list of test suites/tests as of v1.1.0 software.

(BST?L)

```
(BST!L001 001 00000 "All Tests")
(BST!L001 001 00001 "Image Processor Board Tests")
(BST!L001 001 00002 "Formatter Tests")
(BST!L001 001 00003 "Active Backplane Tests")
(BST!L001 001 00004 "Video Path Tests")
(BST!L111 "--END--")
```

(BST+TEST?L)

```
(BST+TEST!L001 001 00000 "ABP: Check FPGA voltages")
(BST+TEST!L001 001 00001 "HIP: Check FPGA voltages")
(BST+TEST!L001 001 00002 "HIP: Verify Undefined pins")
(BST+TEST!L001 001 00003 "HIP: Memory Test")
(BST+TEST!L001 001 00004 "CFB138: Check FPGA voltages")
(BST+TEST!L001 001 00005 "CFB138: Memory Test")
(BST+TEST!L001 001 00006 "CFB138: EEPROM Test")
(BST+TEST!L001 001 00007 "ABP: Test side channel to HIP")
(BST+TEST!L001 001 00008 "HIP: Test side channel between scaler and the warp, CFB, and
between the warp & CFB")
(BST+TEST!L001 001 00009 "Video Path: CRC check between option cards an input FPGA")
(BST+TEST!L001 001 00010 "Video Path: CRC check between input FPGA and the formatters")
(BST+TEST!L111 "--END--")
```

Run all tests successfully.

(BST 0)

```
(BST!000 "--OK--")
```


Example of failed tests within the All Tests test suite:

```
(BST 0)
(BST!001 "Fail" "no response on pin 1")
(BST!002 "Fail" "no additional details")
(BST!000 "Fail")
```

Example of failing test 1:

```
(BST+TEST 1)
(BST+TEST!001 "Fail" "no response on pin 1")
```

CCA–Color Adjustment

Configures the color adjustments for the projector. Use this command to also set the native colors for the projector.

Commands

Command	Description	Values
CCA+SLCT <value>	Sets the color table.	0 = Max Drives Turns off all color adjustments, projector runs at maximum brightness 1 = Color Temperature Selects color adjustments based on a color temperature 2 = HD Video (ITU-RBT.709) 3 = Custom settings
CCA+CTMP <value>	Sets the color temperature of the projector. This is only available if the projector is configured to use Color Temperature for its color table.	3200 to 9300

Command	Description	Values
CCA+RDCX <x coordinate for red> CCA+RDCY <y coordinate for red> CCA+GNCX <x coordinate for green> CCA+GNCY <y coordinate for green> CCA+BLCX <x coordinate for blue> CCA+BLCY <y coordinate for blue> CCA+WHCX <x coordinate for white> CCA+WHCY <y coordinate for white>	Defines a custom color table using x,y coordinates, scaled by a factor of 10,000. For example, an x value of 3350 corresponds to x=0.3350 in the CIE 1931 chromaticity scale.	The valid range for each value depends on which of the Red/Green/Blue point is being adjusted.
CCA+GOFR <green of red saturation value> CCA+BOFR <blue of red saturation value> CCA+ROFG <red of green saturation value> CCA+BOFG <blue of green saturation value> CCA+ROFB <red of blue saturation value> CCA+GOFB <green of blue saturation value>	Defines a custom color table using saturation values. Each control represents a percentage of each native RGB component needed to produce a target RGB space.	-1000 to 1000, where 1000 = 100% A negative value reduces the influence of the component by scaling up the other two components.
CCA+ROFR <red of red saturation value> CCA+GOFG <green of green saturation value> CCA+BOFB <blue of blue saturation value>	Defines a custom color table using saturation values. Each control represents a percentage of each native RGB component needed to produce a target RGB space. <ul style="list-style-type: none"> • Red of red is equivalent to red of white. • Green of green is equivalent to green of white. • Blue of blue is equivalent to blue of white. 	0 to 1000, where 1000 = 100%
CCA+ROFW <red of white saturation value> CCA+GOFW <green of white saturation value> CCA+BOFW <blue of white saturation value>	Defines a custom color table using saturation values. Each control represents a percentage of each native RGB component needed to produce a target RGB space.	0 to 1000, where 1000 = 100%

Command	Description	Values
CCA+RDPX <x coordinate for red> CCA+RDPY <y coordinate for red> CCA+GNPX <x coordinate for green> CCA+GNPY <y coordinate for green> CCA+BLPX <x coordinate for blue> CCA+BLPY <y coordinate for blue> CCA+WHPX <x coordinate for white> CCA+WHPY <y coordinate for white>	Sets the native color primaries for the projector using the x,y coordinate form, scaled by a factor of 10,000. For example, an x value of 3350 corresponds to x=0.3350 in the CIE 1931 chromaticity scale.	The valid range for each value depends on which of the Red/Green/Blue/White point is being adjusted.
CCA+COPY <value>	Copies the values from one of the other pre-defined color tables into the custom color table.	0 = Max Drives 1 = Color Temperature 2 = HD Video (ITU-RBT.709)
CCA+SAVE	Saves the current primary settings (for example, CCA+RDPX, and so on) as the new default color primary settings. Save these settings after calibrating the color primaries (such as measuring the primary x,y coordinates using a spectroradiometer or similar equipment).	0 = Disable the function 1 = Enable the function
CCA+RSET	Resets the native color primary settings to their defaults. If primary settings have not been saved (CCA+SAVE), this resets the primary settings to hard-coded defaults.	-

Examples

Use a custom color table.

(CCA+SLCT 3)

Reset values to "HD Video (ITU-R BT.709)".

(CCA+COPY 2)

Change the x-coordinate of the custom color table to 0.6753.

(CCA+RDCX 6753)

Save the current color primary settings as the new calibrated defaults.

(CCA+SAVE)

Reset the color primary settings to the saved calibrated defaults.

(CCA+RSET)

CHA-Channel

Changes the current channel.

Commands

Command	Description	Values
CHA?L	Returns a list of available channels.	-
CHA <channel>	Selects a specified channel.	channel = One of the indices listed in CHA?L

Examples

Retrieve the list of available channels.

(CHA?L)

```
(CHA!L001 001 00001 "Four-Port (slot 1,2)")
(CHA!L001 001 00002 "Four-Port (slot 3,4)")
(CHA!L001 001 00003 "Four-Port (slot 1,2,3,4) (120Hz)")
(CHA!L001 001 00004 "Four-Port, Dual-Input 3D (slot 1,2,3,4) (120Hz)")
(CHA!L001 001 00011 "Two-Port (slot 1,2)")
(CHA!L001 001 00012 "Two-Port (slot 3,4)")
(CHA!L001 001 00017 "Two-Port, Dual-Input 3D (slot 1,2)")
(CHA!L001 001 00018 "Two-Port, Dual-Input 3D (slot 3,4)")
(CHA!L001 001 00019 "Two-Port, Dual-Input 3D (slot 1,2,3,4) (120Hz)")
(CHA!L001 001 00021 "One-Port (slot 1)")
(CHA!L001 001 00022 "One-Port (slot 2)")
(CHA!L001 001 00023 "One-Port (slot 3)")
(CHA!L001 001 00024 "One-Port (slot 4)")
(CHA!L001 001 00025 "One-Port, Dual-Input 3D (slot 1)")
(CHA!L001 001 00026 "One-Port, Dual-Input 3D (slot 2)")
(CHA!L001 001 00027 "One-Port, Dual-Input 3D (slot 3)")
(CHA!L001 001 00028 "One-Port, Dual-Input 3D (slot 4)")
(CHA!L001 001 00029 "One-Port, Dual-Input 3D (slot 1,2)")
(CHA!L001 001 00030 "One-Port, Dual-Input 3D (slot 3,4)")
(CHA!L111 "--END--")
```

CLE–Color Enable

Enables specific colors in the video path.

Commands

Command	Description	Values
CLE <color>	Enables specific colors in the video path.	0 = White (all colors on) 1 = Red 2 = Green 3 = Blue 4 = Yellow (red and green on) 5 = Cyan (green and blue on) 6 = Magenta (red and blue on)

CSP–Color Space Selection

Changes the color space of the active signal on the screen.



This applies to any channel selected, not per channel.

Commands

Command	Description	Values
CSP <color space>	Changes the color space of the active signal on the screen.	0 = Auto Detect—Automatically sets the color space based on information in the signal. (Default) 1 = RGB—Forces the color space to RGB regardless of what is detected in the signal. 2 = YCbCr HDTV (ITU-RBT.709)—Forces the color space to YCbCr HDTV regardless of what is detected in the signal. 3 = RGB (Limited Range)

Examples

Set the color space to RGB irrespective of which channel is selected.

(CSP 1)

Set the projector to always automatically detect the color space.

(CSP 0)

DEF–Factory Defaults

Resets the projector to its factory default values.



Note the following about the command:

- Only available while the projector is in standby or cooling down.
- The projector must be AC cycled for this command to take effect.

Commands

Command	Description	Values
DEF 111	Performs the factory default command.	111—Must be entered exactly as is

Examples

Reset the projector to factory defaults.

(DEF 111)

```
(65535 00000 FYI00919 "All settings have been restored to their factory defaults.
Reboot is required to take effect.")
```

DTL–Sharpness

Adjusts the sharpness of scaled video to alter the amount of visible detail. This command does not affect unscaled video.

Commands

Command	Description	Values
DTL <value>	Adjusts the sharpness of scaled video to alter the amount of visible detail.	Lower values = Soften the image 50 = Applies a moderate amount of filtering to the image (Default) Higher values = Sharpen the image

EBB–Black Level Blending

Selects the black level blend to use on the projector.

By default, black level blends are not on the projector. Use Twist (or Autocal) to add edge blends to the projector.

Commands

Command	Description	Values
EBB+SLCT?L	Retrieves a list of available black level blends.	-
EBB+SLCT <value>	Selects the black level blend to use on the projector.	0 = Turns off black level blending 1-4 = Selects one of the four black level blends, if available

EBL–Edge Blending Selection

Selects the edge blend to use on the projector.

By default, edge blends are not on the projector. Use Twist (or Autocal) to add edge blends to the projector.

Commands

Command	Description	Values
EBL+SLCT?L	Retrieves a list of available edge blends.	-
EBL+SLCT <value>	Selects the edge blend to use on the projector.	0 = Turns off edge blending 1-4 = Selects one of the four edge blends, if available

EDO–EDID Override

Configures which EDID is presented using inputs that support EDIDs (such as DisplayPort, HDMI, DVI, and so on).



Use this command to configure what the projector advertises regarding the type of signals it accepts.

This command does not need to be set to accept a particular type of signal.

Commands

Command	Description	Values
EDO <rate>	Defines the expected frame rate regardless of the active window size of the signal.	24 25 30 48 50 60 (Default)
EDO+COLM <value>	Defines the expected active window size of the incoming signal.	0 = Standard (quadrants) (2048x1080 / 1920x1080) 1 = Two Column (2048x2160 / 1920x2160) 2 = Four Column (1024x2160 / 960x2160)

EME–Enable Asynchronous Serial Messages

Enables or disables the asynchronous serial messages that the projector occasionally transmits.

Commands

Command	Description	Values
EME <0 1>	Enables or disables asynchronous serial messages.	0 = Disables all asynchronous FYI/ERR serial messages 1 = Enables asynchronous FYI/ERR serial messages (Default)

ETP–Engine Test Pattern

Enables or disables the engine diagnostic test patterns.

Commands

Command	Description	Values
ETP <index>	Enables the engine diagnostic test patterns, indicated by the <index> parameter.	0 = Flat Black 1 = Green 2 = Red 3 = Blue 4 = White 5 = 8x8 Green Checker 6 = 8x8 Red Checker

Command	Description	Values
		7 = 8x8 Blue Checker 8 = 8x8 White Checker 9 = Convergence Border & Cross (Green) 10 = Convergence Border & Cross (Red) 11 = Convergence Border & Cross (Blue) 12 = Convergence Border & Cross (White) 13 = Convergence Border & Cross (Multi-color) 14 = Convergence Border & Square (Green) 15 = Convergence Border & Square (Red) 16 = Convergence Border & Square (Blue) 17 = Top Blue, Bottom Black 18 = Left Blue, Right Black 19 = Top Green, Bottom Black 20 = Left Green, Right Black 21 = Top Red, Bottom Black 22 = Left Red, Right Black 29 = Convergence Border & Cross (Multi-color2) (green/red colors are swapped) 45 = Convergence Border & Cross (Multi-color3) (green/blue colors are swapped) 238 = Color Bars 239 = Edge Blend Grid (Green) 240 = Edge Blend Grid (Red) 241 = Edge Blend Grid (Blue) 242 = Edge Blend Grid (White) 243 = 17 Point 244 = Magenta 245 = Cyan 246 = Yellow 247 = Diagonal Lines 248 = Dark Segmented Ramp 249 = Bright Segmented Ramp 255 = Off

EVT-Event Manager

Retrieves a list of significant log messages for the current AC cycle from the projector.

Commands

Command	Description	Values
EVT	Returns all events starting from the most recent event on the projector back to AC start. (Read-only)	-
EVT <max>	Returns at most <max> events starting from the most recent event on the projector back to AC start. (Read-only)	max = Maximum number of events to return
EVT <start timestamp>	Returns all events from <start timestamp> back to current time. The timestamp has a format of yyyy-mm-dd hh:mm:ss. (Read-only)	start timestamp = String in the following format: yyyy=mm-dd hh:mm:ss
EVT <start timestamp> <end timestamp>	Returns all events from <end timestamp> back to <start timestamp>. The timestamps have a format of yyyy-mm-dd hh:mm:ss. (Read-only)	start timestamp = String in the following format: yyyy=mm-dd hh:mm:ss end timestamp = String in the following format: yyyy=mm-dd hh:mm:ss

Examples

Retrieve all events since last AC start.

(EVT)

```
(EVT!000 "2013-03-17 04:47:18.340" "OK" "Setting Time to 06:47:17")
(EVT!001 "2013-03-17 04:01:13.860" "Error" "(SST+TEMP?003) Lamp
    Exhaust Temperature (Temp 3) = Communication fault (shutdown)")
(EVT!002 "2013-03-17 04:01:13.855" "Error" "(SST+TEMP?002) Air
    Intake Temperature (Temp 2) = Communication fault (shutdown)")
(EVT!003 "2013-03-17 04:01:13.824" "Error" "(SST+TEMP?000) Integrator
    Rod Temperature (Temp 1) = Communication fault (shutdown)")
(EVT!004 "2013-03-17 04:01:12.663" "Error" "(SST+VERS?017) Lamp Power
    Supply Version = Detection fault")
(EVT! "--END--")
```

Retrieve two most recent events.

(EVT 2)

```
(EVT!000 "2013-03-17 04:47:18.340" "OK" "Setting Time to 06:47:17")
(EVT!001 "2013-03-17 04:01:13.860" "Error" "(SST+TEMP?003) Lamp
    Exhaust Temperature (Temp 3) = Communication fault (shutdown)")
(EVT! "--END--")
```

Retrieve all events from a specific point in time until now.

```
(EVT "2013-03-17 04:01:13")
(EVT!000 "2013-03-17 04:47:18.340" "OK" "Setting Time to 06:47:17")
(EVT!001 "2013-03-17 04:01:13.860" "Error" "(SST+TEMP?003) Lamp
    Exhaust Temperature (Temp 3) = Communication fault (shutdown)")
(EVT!002 "2013-03-17 04:01:13.855" "Error" "(SST+TEMP?002) Air
    Intake Temperature (Temp 2) = Communication fault (shutdown)")
(EVT!003 "2013-03-17 04:01:13.824" "Error" "(SST+TEMP?000) Integrator
    Rod Temperature (Temp 1) = Communication fault (shutdown)")
(EVT! "--END--")
```

Retrieve all events between two specific points in time.

```
(EVT "2013-03-17 04:01:08" "2013-03-17 04:01:12")
(EVT!004 "2013-03-17 04:01:12.663" "Error" "(SST+VERS?017) Lamp Power
    Supply Version = Detection fault")
(EVT! "--END--")
```

FCS–Lens Focus Position Adjustment

Sets the lens focus to an absolute position. This requires a focus motor on the lens for it to work.

Commands

Command	Description	Values
FCS <position>	Adjusts the lens focus to the specified position.	-2000 to 2800

Examples

Move lens focus to position 500.

```
(FCS 500)
```

FRD–Frame Delay

Sets the delay between the input sync timing and the output sync timing, measured in 1/1000^{ths} of a frame (based on the input frame rate). The actual delay can vary based on the amount of processing applied to the image.

Commands

Command	Description	Values
FRD <delay>	Sets the frame delay, measured in 1/1000 ^{ths} of a frame.	1000 to 3000 2000 = 2 frames(Default)
FRD+STAT?	Returns the actual frame delay in 1/1000 ^{ths} of a frame. This value may be higher than the required delay as the minimum allowed delay differs for each of the various channel configurations. (Read-only)	-
FRD+TIME?	Returns a string representation of the actual frame delay, in milliseconds. Note: This representation in milliseconds is approximate and is for reference only.	-

Examples

Set the frame delay to 2.25 frames.

(FRD 2250)

Set the frame delay to 1.1 frames.

(FRD 1100)

Query the actual frame delay.

(FRD+STAT?)

(FRD+STAT!1250)

Query the actual frame delay, in ms.

(FRD+TIME?)

(FRD+TIME! "33.33")

FRZ–Image Freeze

Freezes the active video or test pattern.

Commands

Command	Description	Values
FRZ <0 1>	Freezes the active video or test pattern.	0 = Disable freezing of current video 1 = Freeze the current video

GAM–Gamma Power Value

Defines the exponent used in a standard Power Law Function. This command is only available if the base gamma curve is set to Power Law Function (see *BGC–Base Gamma Curve* on page 7).

Commands

Command	Description	Values
GAM <exponent>	Sets the exponent for the power law function used for the gamma transfer function.	1000 to 3000

Examples

Set the base gamma curve function to 2.6

(**GAM 2600**)

Set the base gamma curve function to 1.0

(**GAM 1000**)

ITP–Internal Test Pattern

Enables or disables test patterns.

Commands

Command	Description	Values
ITP <index>	Enables or disables test patterns.	0 = Off 1 = Grid 2 = Grey Scale 16 3 = Flat White 4 = Flat Grey 5 = Flat Black 6 = Checker 7 = 17 Point 8 = Edge Blend 9 = Color Bars 10 = Multi Color 11 = RGBW Ramp 12 = Horizontal Ramp 13 = Vertical Ramp 14 = Diagonal Ramp 15 = Square Grid 16 = Diagonal Grid 17 = Prism / Convergence 18 = Maximum Activity 19 = FLIR
ITP+GREY <grey level>	Defines the shade of grey for the Flat Grey test pattern.	0 to 4095 2048 (Default)
ITP+RMPM <speed>	Defines the motion speed used for the Horizontal Ramp, Vertical Ramp, and Diagonal Ramp test patterns.	0 (Default) to 100
ITP+RMPS <slope>	Defines the slope used for the Horizontal Ramp, Vertical Ramp, and Diagonal Ramp test patterns.	1 (Default) to 5
ITP+RMPL <grey level>	Defines the starting (top/left) grey-level used for the Horizontal Ramp, Vertical Ramp, and Diagonal Ramp test patterns. This setting has no effect when the ramp is moving (such as ITP+RMPM is non-zero).	0 (Default) to 4095
ITP+GRDP <pitch>	Defines the spacing between lines used for the Square Grid and Diagonal Grid test patterns.	2 to 127 32 (Default)
ITP+GRDC <0 1>	Enables multi-color or white-on-black grids for the Square Grid or Diagonal Grid test patterns.	0 = Multi-color (Default) 1 = White-on-black
ITP+GRDM <0 1>	Enables moving or static grid for the Square Grid or Diagonal Grid test patterns.	0 = Static (Default) 1 = Moving

LCB–Lens Motor Calibration

Calibrates all of the lens motors.

Commands

Command	Description	Values
LCB 1	Runs calibration on all lens motors.	-
LCB+HOME	Moves the lens to position 0 along the horizontal and vertical axes.	-

Examples

Start calibration:

(LCB 1)

Move the lens back to the home position:

(LCB+HOME)

LHO–Lens Horizontal Position Adjustment

Sets the lens horizontal location to an absolute position.

Commands

Command	Description	Values
LHO <position>	Adjusts the horizontal location of the lens to the specified position.	-1600 to 1600

Examples

Move the lens to position 500 on the horizontal axis.

(LHO 500)

LMV–Lens Move

Adjusts all aspects of the lens position using a single command. It can also be used to move the lens to a relative position or to start and stop the motors arbitrarily.

Commands

Command	Description	Values
LMV <horizontal> <vertical> <zoom> <focus>	Moves the lens to an absolute position as specified by each of the four arguments.	Horizontal maximum range = -1600 to 1600 Vertical maximum range = -1600 to 1600 Zoom/focus maximum = Dependent on type of lens and calculated during lens calibration
LMV+HSTP <relative steps> LMV+VSTP <relative steps> LMV+FSTP <relative steps> LMV+ZSTP <relative steps>	Moves the lens a relative number of steps on the specified axis. HSTP = Horizontal VSTP = Vertical FSTP = Focus ZSTP = Zoom	steps = Either negative or positive numbers The maximum absolute value is dictated by the motor's current location and the range of the axis (see the LMV command).
LMV+HRUN <-1 0 1> LMV+VRUN <-1 0 1> LMV+FRUN <-1 0 1> LMV+ZRUN <-1 0 1>	Starts and stops each motor: HRUN = Horizontal VRUN = Vertical FRUN = Focus ZRUN = Zoom	-1 = Moves the motor in reverse 0 = Stops the motor 1 = Moves the motor forward

Examples

Set the lens to H: 1000, V: 1500, Z: 500, F: 500.

(**LMV 1000 1500 500 500**)

Start to move horizontal motor toward positive max position.

(**LMV+HRUN 1**)

Stop the vertical motor.

(**LMV+VRUN 0**)

Start moving the zoom motor towards the negative max position.

(**LMV+ZRUN -1**)

Move the horizontal motor 45 steps in the positive direction.

(**LMV+HSTP 45**)

LOE–Video Loop Out Enable

Enables or disables video loop out on the following cards: THIC, 3GIC, and TDPIC.

Commands

Command	Description	Values
LOE <0 1>	Enables or disables video loop out. Note: Applies to all of the option cards in the projector.	0 = Disables video loop out 1 = Enables video loop out (Default)

LVO–Lens Vertical Position Adjustment

Sets the lens vertical location to an absolute position.

Commands

Command	Description	Values
LVO <position>	Adjusts the vertical location of the lens to the specified position.	-1600 to 1600

Examples

Move the lens to position 500 on the vertical axis.

(LVO 500)

NET–Network Setup

Changes the network configuration for the Ethernet port. By default, DHCP support is turned on.

Commands

Command	Description	Values
NET <ip> <subnet> [gateway]	Sets the projector network settings as specified.	All three arguments are strings and the gateway is optional.

Command	Description	Values
NET+DGRP <group>	Sets the device group name for the projector. This can help simplify broadcast searching by organizing projectors into groups, particularly if a large number of projectors are on the same local network.	-
NET+DHCP 1	Enables DHCP. To turn off DHCP support, switch to a static IP by using the base command.	-
NET+ETH0?	Returns the projector IP address. (Read-only)	-
NET+GATE?	Returns the projector gateway address. (Read-only)	-
NET+HOST <name>	Sets the name for the projector. With this set, devices on the same network subnet as the projector can connect to it using the name: <name>.local.	-
NET+MAC0?	Returns the MAC address of the Ethernet port. (Read-only)	-
NET+PORT?	Returns the TCP port used for the Christie Serial Protocol over Ethernet. (Read-only)	1024 to 49151 (with some exceptions) 3003 = Reserved on the projector and cannot be used for the Christie Serial Protocol
NET+SUB0?	Returns the projector netmask. (Read-only)	-

Examples

Set the static IP address to 192.168.1.100, with a netmask of 255.255.255.0, and no gateway:

```
(NET "192.168.1.100" "255.255.255.0")
```

Turn on DHCP support:

```
(NET+DHCP 1)
```

NTR—Network Routing

Enables or disables routing of Christie Protocol messages between the RS232, RS422, and Ethernet ports.



RS232-IN and RS232-OUT are always joined, regardless of the NTR setting.

Commands

Command	Description	Values
NTR <value>	Enables or disables routing of Christie Protocol messages.	0 = Separate (Default) 1 = RS232 and RS422 joined 2 = RS232 and Ethernet joined 3 = All joined (includes USB)

Examples

Route messages between the RS232 ports to/from the RS422 port.

(NTR 1)

PNG-Ping

Returns basic projector information to the user, including the type of device and main software version.

Commands

Command	Description	Values
PNG?	Returns basic projector information (Read-only): <type> <major> <minor> <build> where Type = 54 (fixed value) Major, Minor, Build = Software version	-

Examples

Send a ping.

(PNG?)

PRO-Profile

Allows selection of a local profile on the projector.

Commands

Command	Description	Values
PRO?L	Returns the list of available local profiles:	-
PRO x	Selects local profile x and applies the profile to the projector. Selecting an empty profile does not do anything.	0 = Default 1 = <custom 1> 2 = <custom 2> 3 = <custom 3> 4 = <custom 4>

PWR–Power

Turns the projector power on and off.

Commands

Command	Description	Values
PWR <0 1>	Turns the projector on or off.	0 = Turns the projector off 1 = Turns the projector on
PWR+ELEC <0 1>	Keep video electronics on in standby, regardless of laser state.	0 = Disables electronics override 1 = Enables electronics override
PWR?	Returns the current power state of the projector: 000 = Power Off 011 = Warming Up 001 = On 010 = Cooling Down	-

Examples

Turn on the projector.

(PWR 1)

Turn off the projector.

(PWR 0)

Return current state of the power to the projector.

(PWR?)

(PWR!000 "Power Off")

RAL—Remote Access Level

Sets the default remote serial protocol access level for any of the serial ports.

Commands

Command	Description	Values
RAL+PRTA <value>	Sets the access level for the RS232-IN port.	0 = No Access—Disables the port
RAL+PRTB <value>	Sets the access level for the RS232-OUT port.	1 = Login Required—Sets read-only access until a separate login is performed
RAL+PRTC <value>	Sets the access level for the RS422 port.	2 = Free Access—Executes commands at the operator level unless a separate login is performed (Default)
RAL+PUSB <value>	Sets the access level for the USB port.	

Examples

Set port to Login Required.

(RAL+PRTC 1)

SHU—Shutter

Opens and closes the shutter. It can also be used check if the shutter is currently opened or closed.



This command may return an incorrect result if the shutter was manually opened or closed.

Commands

Command	Description	Values
SHU <0 1>	Opens or closes the shutter.	0 = Opens the shutter 1 = Closes the shutter

Examples

Open the shutter.

(SHU 0)

Close the shutter.

(SHU 1)

Get the state of the shutter (0 for open, 1 for closed).

(SHU?)

SNM–SNMP Configuration

Configures SNMP support for the projector.

Commands

Command	Description	Values
SNM+TIP1 <ip address> SNM+TIP2 <ip address> SNM+TIP3 <ip address>	Sets up to three IP addresses for traps to be sent.	ip address = String value 0.0.0.0 disables notifications (Default)
SNM+READ <password>	Sets the password for SNMP notifications.	password = String value Default password = private
SNM+LAMP <0 1>	Enables or disables Lamp State SNMP traps.	0 = Disables Lamp State SNMP traps 1 = Enables Lamp State SNMP traps
SNM+LIFE <0 1>	Enables or disables Lamp End-Of-Life SNMP traps.	0 = Disables Lamp End-Of-Life SNMP traps 1 = Enables Lamp End-Of-Life SNMP traps
SNM+POWR <0 1>	Enables or disables Power On/Off SNMP traps.	0 = Disables Power On/Off SNMP traps 1 = Enables Power On/Off SNMP traps
SNM+STAL <0 1>	Enables or disables Fan Stall SNMP traps.	0 = Disables Fan Stall SNMP traps 1 = Enables Fan Stall SNMP traps
SNM+THRM <0 1>	Enables or disables Thermal warning/error SNMP traps	0 = Disables Thermal warning/error SNMP traps 1 = Enables Thermal warning/error SNMP traps

SOR–Screen Orientation

Changes the orientation of the displayed image.

Commands

Command	Description	Values
SOR <value>	Changes the orientation of the displayed image.	0 = Front Projection (Default) 1 = Rear Projection 2 = Front Projection Inverted 3 = Rear Projection Inverted

SST-Status

Returns status information about the projector in read-only mode. See the Status System documentation for a list of items and their possible values.

Each item is listed in the following format:

(SST+<group>!<index> <state> "<value>" "<description>")

where:

- <group> is the four letter identifier of the status system group the item belongs to.
- <index> is the index value of the status item within the group.
- <state> is the condition of the status item:
 - 000 = OK
 - 001 = Warning
 - 002 = Error
- <value> is the value of the status item.
- <description> is the descriptive name of the status item.

Commands

Command	Description	Values
SST?	Returns all status items.	-
SST+<group>?	Returns all status items within the specified four-letter group identifier.	-
SST+<group>?<index>	Returns a specific status item within the specified four-letter group identifier.	-

Examples

The following example was reduced for brevity:

(SST+TEMP?)

...

```
(SST+TEMP!000 000 "21 °C" "Integrator Rod Temperature (Temp 1)")
(SST+TEMP!002 000 "21 °C" "Air Intake Temperature (Temp 2)")
(SST+TEMP!003 000 "21 °C" "Lamp Exhaust Temperature (Temp 3)")
(SST+TEMP!020 000 "28 °C" "Environmental Board Temperature")
...
```

Return item 20 of the temperature group.

```
(SST+TEMP?20)
(SST+TEMP!020 000 "28 °C" "Environmental Board Temperature")
```

SZP–Size and Position

Changes the aspect ratio of the display.

By default, the projector scales all video to the full screen with the exception of 16:9 content. 16:9 content is scaled to 3840x2160 with black pillar boxes on either side.

Commands

Command	Description	Values
SZP <value>	Changes the aspect ratio of the display.	0 = Allows the projector to determine when to scale video (Default) 1 = None 2 = Scales all content to the full screen

TMD–Time and Date

Sets the date and time in the real-time clock.

Commands

Command	Description	Values
TMD+TIME <time>	Sets the time for the clock.	time = String in the following format: hh:mm:ss
TMD+DATE <date>	Sets the date for the clock.	date = String in the following format: YYYY/MM/DD

Examples

Set the time to 3pm.

(TMD+TIME "15:00:00")

Set the date to September 17th, 2014.

(TMD+DATE "2014/09/17")

Get the local time.

(TMD+TIME?)

UID–User ID

Changes the access level of the currently connected session.

Commands

Command	Description	Values
UID <username> <password>	Logs in using the specified user name and password.	-

Examples

Login as service using the default password.

(UID "service" "service")

WRP–Warp Selection

Selects the warp map to use on the projector.

By default, warp maps are not on the projector. Use Twist (or Autocal) to add warp maps.

Commands

Command	Description	Values
WRP+SLCT?	Retrieves a list of available warp maps.	-
WRP+SLCT <value>	Changes the warp map to use on the projector.	0 = Turns off warping 1-4 = Selects one of four warp maps, if available

ZOM–Lens Zoom Position Adjustment

Sets the lens zoom to an absolute position. This requires a zoom motor on the lens for it to work.

Commands

Command	Description	Values
ZOM <position>	Adjusts the lens zoom to the specified position.	Valid range changes based on calibration.
ZOM?m	Returns the current minimum and maximum values for the zoom position based on the last lens calibration performed.	-

Examples

Get the current minimum/maximum values for the zoom axis.

(ZOM?m)

(ZOM!M-2400 900)

Move the lens to position 500 for the zoom motor.

(ZOM 500)

Asynchronous messages

The projector can generate some asynchronous messages. The following lists examples of each message, including why and when they are generated.



Bolded and underlined text indicates a fixed part of the message.

Type	Message	Description
Card Detected	(<u>65535 0000 FYI01901 "Card x detected"</u>)	Triggered when a new card is detected in slot X while the video electronics are already on.
Card Removed	(<u>65535 0000 FYI01901 "Card x removed"</u>)	Triggered when a card is removed from slot X while the video electronics are on.
Date/Time	(<u>65535 0000 FYI00916</u> "Setting Date to 2014/06/20")	Generated when the date or time are changed, respectively.
	(<u>65535 0000 FYI00916</u> "Setting Time to 00:00:00")	
Factory defaults	(<u>65535 0000 FYI00919</u> "All settings have been restored to their factory defaults. Reboot is required to take effect.")	Generated when a factory default has been performed on the projector.
Networking	(<u>65535 0000 FYI00915</u> "Configured network: IP:192.168.228.6 Mask: 255.255.252.0 Gateway: 192.168.228.1")	Generated when the network settings have changed. Network settings can change due to a number of specific events such as: <ul style="list-style-type: none"> • Operator changes the network settings (through any of the standard interfaces). • DHCP lease is renewed. • The network cable has been unplugged or plugged in.
Status	(<u>65535 0000 FYI00000</u> " <u>(SST+LAMP?001)</u> Lamp Hours = 00:00 (h:m)")	Generated when a status item changes from an error or warning state to an OK state.
	(<u>65535 0000 ERR00000 "System Warning: (SST+LAMP?001)</u> Lamp Hours = N/A")	Generated when a status item changes from an OK or error state to a warning state.
	(<u>65535 0000 ERR00000 "System Error: (SST+VERS?003)</u> Image Processor HW Version = Detection Fault")	Generated when a status item changes from an OK or warning state to an error state.

Corporate offices

USA – Cypress
ph: 714-236-8610

Canada – Kitchener
ph: 519-744-8005

Consultant offices

Italy
ph: +39 (0) 2 9902 1161

Worldwide offices

Australia
ph: +61 (0) 7 3624 4888

Brazil
ph: +55 (11) 2548 4753

China (Beijing)
ph: +86 10 6561 0240

China (Shanghai)
ph: +86 21 6278 7708

Eastern Europe and
Russian Federation
ph: +36 (0) 1 47 48 100

France
ph: +33 (0) 1 41 21 44 04

Germany
ph: +49 2161 664540

India
ph: +91 (080) 6708 9999

Japan (Tokyo)
ph: 81 3 3599 7481

Korea (Seoul)
ph: +82 2 702 1601

Republic of South Africa
ph: +27 (0)11 510 0094

Singapore
ph: +65 6877-8737

Spain
ph: + 34 91 633 9990

United Arab Emirates
ph: +971 4 3206688

United Kingdom
ph: +44 (0) 118 977 8000