
Software Release Notes

Access II Series display panels firmware v7.88.1.0

This document provides firmware update instructions and describes known and fixed issues in firmware version 7.88.1.0 for the Access II Series display panels.

Affected products

The following products are affected.

- UHD552-L
- UHD652-L
- UHD752-L
- UHD862-L
- UHD982-P

New features

The following new features and enhancements are included in this release.

- Resolved an issue with the FTI.
- Resolved the color temperature issue when in Warm mode.
- Resolved an issue with the input changing after the Input info page is accessed.
- Updated general bug fixes related to network and RS232 commands.

Upgrading the firmware from USB

Install the new firmware to upgrade the display panels.

1. Download the latest software from www.christiedigital.com and unzip the file.
2. Navigate to `core_update/access_7.88.1.0_mb130.bin`.
3. Copy the `access_7.88.1.0_mb130.bin` file to the root of a USB storage device.
4. Connect the USB storage device to the display panel.
5. If the Media Browser is displayed, to close it press **Exit** on the remote.
6. On the display panel remote, press **Menu > 1505**.
7. In the confirmation dialog, select **Yes**.

During the upgrade process the display panel restarts. After the display panel restarts, while the upgrade finishes nothing is displayed on the panel and a red LED in the IR receiver blinks. The process may take a few minutes to complete.

Updating the profile

Apply settings to the display panel.

1. Download the latest software from www.christiedigital.com and unzip the file.
2. On the USB storage device, at the root create a folder called **Profile**.
3. Copy the `MB130_swprofile.bin` and `MB130_hwprofile.bin` files to the Profile folder.
4. Connect the USB storage device to the display panel USB-1 port.
5. If the Media Browser is displayed, to close it press **Exit** on the remote.
6. On the display panel remote, press **Menu > 4725**.
7. Select **USB operations** and on the remote press **OK**.
8. Exit the Service Menu and power off the panel.
9. Power on the panel.
10. Using the remote, navigate to **Menu > Signage Settings > First Time Installation**.
11. Press **OK**.
12. In the confirmation dialog, select **Yes**.
13. Confirm the First Time Installation steps.
During the upgrade process the display panel restarts. After the display panel restarts, while the upgrade finishes nothing is displayed on the panel and a red LED in the IR receiver blinks. The process may take a few minutes to complete.

Built-in password

Note the following about the built-in password in the firmware:

Version 7.69.3.0 firmware and onward has a built-in password to comply with the California Civil Code Section 1798.91.04. The default password is 0000. Change the pin to any four-numeric digits.

Use the `SETUSERSECLEVEL ADMIN "password"` API command to unlock the serial or Ethernet connection. After the command is sent, you can send other API commands; however, the panel does not send a reply if you do not initially send the `SETUSERSECLEVEL ADMIN "password"` command.

To reset the password to factory default, select **Menu 4725 > Perform factory reset**.

Product documentation

For installation, setup, and user information, see the product documentation available on the Christie website. Read all instructions before using or servicing this product.

1. Access the documentation from the Christie website:
 - Go to this URL: <https://bit.ly/2GniMjQ>.
 - Scan the QR code using a QR code reader app on a smartphone or tablet.



2. On the product page, select the model and switch to the **Downloads** tab.

Related documentation

Additional information on the LCD panels is available in the following documents.

- *Access II Series LCD Panels Product Safety Guide (P/N: 020-001848-XX)*
- *Access II Series LCD Panels External Controls (P/N: 020-001853-XX)*
- *UHD552-L Service Guide (P/N: 020-001844-XX)*
- *UHD652-L Service Guide (P/N: 020-001845-XX)*
- *UHD752-L Service Guide (P/N: 020-001846-XX)*
- *UHD862-L Service Guide (P/N: 020-001847-XX)*
- *UHD982-P Service Guide (P/N: 020-001709-XX)*

Technical support

Technical support for Christie Enterprise products is available at:

- North and South America: +1-800-221-8025 or Support.Americas@christiedigital.com
- Europe, Middle East, and Africa: +44 (0) 1189 778111 or Support.EMEA@christiedigital.com
- Asia Pacific (support.apac@christiedigital.com):
 - Australia: +61 (0)7 3624 4888 or tech-Australia@christiedigital.com
 - China: +86 10 6561 0240 or tech-supportChina@christiedigital.com
 - India: +91 (80) 6708 9999 or tech-India@christiedigital.com
 - Japan: 81-3-3599-7481
 - Singapore: +65 6877-8737 or tech-Singapore@christiedigital.com
 - South Korea: +82 2 702 1601 or tech-Korea@christiedigital.com
- Christie Professional Services: +1-800-550-3061 or NOC@christiedigital.com